Fundamentals of telecommunications

Training materials for wireless trainers



Goals

To present the basics concepts of telecommunication systems with focus on digital and wireless

Basic Concepts

•Signal

Analog, Digital, Random

- •Sampling
- Bandwidth
- •Spectrum
- Noise
- Interference
- •Channel Capacity
- •BER
- Modulation
- Multiplexing
- Duplexing

Telecommunication Signals

Telecommunication signals are variation over *time* of voltages, currents or light levels that carry information.

For analog signals, these variations are directly proportional to some physical variable like sound, light, temperature, wind speed, etc.

The information can also be transmitted by digital signals, that will have only two values, a digital *one* and a digital *zero*.

Telecommunication Signals

Any analog signal can be converted into a digital signal by appropriately *sampling* it.

The sampling frequency must be at least twice the maximum frequency present in the signal in order to carry *all* the information contained in it.

Random signal are the ones that are unpredictable and can be described only by statistical means.

Noise is a typical random signal, described by its mean power and frequency distribution.

Examples of Signals



Sinusoidal Signal



A = Amplitude, volts

- $w_o = 2\pi f_o$, angular frequency in radians
- f_o = frequency in Hz
- T = period in seconds, $T = I/f_o$
- Θ = Phase

Signals and Spectra



Spectral analysis and filters



Filter Types



- Bandpass
- Lowpass
- High Pass
- Bandstop

Sampling



Analog Signal

Sampling Circuit S

Sampled Signal

The sampled signal can be quantized and coded to convert it to a digital signal.

This is normally done with an ADC (Analog to Digital Converter). The recovery of the original signal is by means of a DAC.

Image Sampling

Normal, 72pixels/inch

Sampled Image, 10 pixels/inch





Why Digital?

Noise does not accumulate when you have a chain of devices like it happens in an analog system: CD Versus Vinyl, VHS Vs DVD.

The same goes for the storing of the information.

- Detection of a digital signal is easier than an analog signal, so digital signal can have greater range.
- Digital signals can use less bandwidth, as exemplified by the "*digital dividend*" currently being harnessed in many countries.
- Digital circuits are easier to design and can achieve greater integration levels than analog circuits.
- Digital signals can be encoded in ways that allow the recover from transmission errors, albeit at the expense of throughput.

Communication System



Signal Delay



- time



Attenuation





Transmitted Signal

Received Signal

Noise in an analog Signal





time



time

Bandwidth Limitation







Interference

Any signal different from the one that our system is designed to receive that is captured by the receiver impairs the communication and is called interference.

Intra-channel interference originates in the same channel as our signal.

Co-channel interference is due to the imperfection of the filters that will let in signals from adjacent channels.

Information Measurement

 $I = \log_2 (I/Pe)$

The information carried by a signal is expressed in bits and is proportional to the logarithm of the inverse of the probability of the occurrence of the corresponding event.

The more unlikely an event to happen, the more information its happening will carry.

Transmitting a message of an event that the receiver already knows carries no information.

The amount of information transmitted in one second is the *capacity* of the channel, expressed in bit/s.

Redundancy

Sending twice the same information is a waste of the system capacity that reduces the *throughput*.

Nevertheless, if an error occurs, the redundancy can be used to overcome the error.

Every error correcting code must use some sort of redundancy.

Channel Capacity



Detection of a noisy signal



time, s

Electrical Noise



Noisy Received Signal 2 1.8 1.6 1.4 1.2 1 0.8 0.6 0.4 0.2 0 time, s Detection error Decision Threshold **Received Sequence** Ċ. D 0 0

1

0

1

0

1

MoDem



Comparison of modulation techniques



Digital Sequence

ASK modulation

FSK modulation

PSK modulation

QAM modulation, changes both amplitude and phase

BER Versus E_b/N_o



From Wikipedia: <u>http://en.wikipedia.org/wiki/Bit_error_rate</u>

Comparison of modulation types BER of 10⁻⁶

Mod.Type	Bits/Symbol	Required E _b /N _o
I6 PSK	4	I8 dB
I6 QAM	4	I5 dB
8 PSK	3	14.5 dB
4 PSK	2	IO.I dB
4 QAM	2	10.1 dB
BFSK		13.5 dB
BPSK		10.5 dB

Multiplexing



Medium sharing techniques



Example: U.S. Television Channels Allocation

Signal Power



CDMA analogy

Two messages superposed, one in yellow and one in blue

A blue filter reveals what is written in yellow

A yellow filter reveals what is written in blue uch like the distance.

TheTropsessacquifild enlands domaduly themited row windoes al autholikionhthailoccuerahong ordinary propagation paths. Occasionally, a site is located atop a high mountain or other location from which it can see a very large distance, so large bis dow is at icgn and racius noust originate locabe Sacgeire induring lard of the yound the industance.

Abstraction and a demodule the second and a demodule the second and a second and a second and a second and a second a se

Types of transmissions

Simplex:

one way only, example: TV Broadcasting

Half-duplex:

the corresponding stations have to take turns to access the medium, example: walkie-talkie. Requires hand-shaking to coordinate access. This technique is called **TDD** (Time Division Duplexing)

Full-duplex:

the two corresponding stations can transmit simultaneously, employing different frequencies. This technique is called **FDD** (Frequency Division Duplexing). A guard band must be allowed between the two frequencies in use.

Conclusions

The communication system must overcome the noise and interference to deliver a suitable replica of the signal to the receiver.

The capacity of the communication channel is proportional to the bandwidth and to the logarithm of the S/N ratio.

Modulation is used to adapt the signal to the channel and to allow several signals to share the same channel. Higher order modulation schemes permit higher transmission rates, but require higher S/N ratio. The channel can be shared by several uses that occupy different frequencies, different time slots or different codes

Thank you for your attention

For more details about the topics presented in this lecture, please see the book Wireless Networking in the Developing World, available as a free download in many languages:

http://wndw.net/

